



DC Brushless Motor Driver IC

PL398V Single coil Smart Motor Driver IC with PWM control

Applications


- Single coil DC brushless motor

Features

- Built-in hall sensor
- Single phase full wave driver
- Soft switching output driver
- Lead angle adjustment
- Speed controllable by DC voltage / direct PWM
- Minimum speed setting
- Quick start
- Locked protection and automatic restart
- Current limit protection
- Thermal protection
- FG/RD output (open drain)
- Built-in Zener diode
- High balance and low thermal drift magnetic sensing
- Low power consumption and high driving efficiency
- RoHS 2.0 compliance

Package:

DFN-10 (3x3x0.75mm)



Specifications

Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Conditions	Rating	Units
Maximum supply voltage	VDDmax		32	V
Allowable power dissipation	Pd	DFN-10	1860	mW
Operating temperature	Ta		-40~+105	°C
Storage temperature	Ts		-50~+150	°C
Max. output current(O1, O2)	IOUTMAX	0.5sec	1200*1	mA
Max. output voltage(O1, O2, FG/RD)	VOUTMAX		32	V
Max. FG/RD output current	IFG/RDMAX		10	mA
Max. PWM input voltage	VPWMMAX		8	V
Max. input voltage(VL, LA)	VINMAX		6	V
VREF output current	IVREF		5	mA
Junction Temperature	Tj		150	°C

*1: Should not exceed Pd