



PT3937

24V Single coil Hall Driver IC with RD output

Applications

- Single coil DC brushless motor
- Support pre-driver application

Features

- Built-in hall sensor
- Single phase full wave driver
- Soft switching output driver
- Motor locked protection and automatic restart
- RD output
- Built-in hysteresis comparator
- Built-in zener diode
- High balance and low thermal drift magnetic sensing
- Low power consumption and high driving efficiency
- Thermal protection

Specifications

Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Conditions	Rating	Units
Maximum supply voltage	VDDmax	10u sec	42	V
Allowable power dissipation	Pd		568 ^{*1}	mW
Operating temperature	Ta		-40~+85	°C
Storage temperature	Ts		-50~+150	°C
Max. output current	I _{OMAX}	0.5sec	1200 ^{*2}	mA
RD output current	I _{RDMAX}		20	mA
RD output voltage	V _{RDMAX}		32	V
Maximum Junction temperature	Tjmax		150	°C

*1: Reduced by 4.54mW for each increase in Ta of 1°C over 25°C When mounted on 50mm x 50mm x 1.6mm glass epoxy board

*2: Should not exceed Pd

Package: TO-92-5pin

